

8258

WHITE	0V)	:	(0V RED	
)	:	(425V BLACK	0.22A
)	:	(850V RED	
BLACK	120V)	:	(0V YELLOW	3A
ORANGE	0V)	:	(5V YELLOW	
)	:	(0V GREEN	4A
)	:	(7.5V GREEN	
BROWN	120V)	:	(0V BROWN	1.5A
)	:	(---ct--- ORANGE	
)	:	(6.3V BROWN	
)	:	(0V BLUE	2.5A
)	:	(---ct--- WHITE	
)	:	(6.3V BLUE	
GREEN/YELLOW)	:	(ELECTROSTATIC SCREEN	

For 240V: Join RED & BLACK. Use BLUE & BROWN
(Isolate both WHITES separately)

For 120V: Join BLUE & BLACK 0V and join RED & BROWN 120V.
(Isolate both WHITES)

For 110V: Join BLUE & BLACK 0V and join both WHITES 110V.
(Isolate RED & Isolate BROWN)

If the White leads are cut short please ensure the TWO wires are joined together in BOTH cases.