

8353

	BLUE	0V	_____)	:			:	(_____	0V ORANGE	
)	:			:	(_____	290V GREY	0.25A
(1)	WHITE	110V	_____)	:			:	(_____	580V ORANGE	
)	:			:	(_____	0V VIOLET	
	RED	120V	_____)	:			:	(_____	130V VIOLET	0.10A
	BLACK	0V	_____)	:			:	(_____	0V PINK	
)	:			:	(---ct---	GREEN	3A
(2)	WHITE	110V	_____)	:			:	(_____	5V PINK	
)	:			:	(_____	0V YELLOW (1)	
	BROWN	120V	_____)	:			:	(_____	6.3V YELLOW (2)	1A
)	:			:	(_____	0V YELLOW (2)	
)	:			:	(_____	6.3V YELLOW (2)	1A
	SCREEN-GREEN/YELLOW		_____)	:			:	(_____	WHITE/RED-SCREEN	

For 240V: Join RED & BLACK. Use BLUE & BROWN
(Isolate both WHITES separately)

For 120V: Join BLUE & BLACK 0V and join RED & BROWN 120V.
(Isolate both WHITES)

For 110V: Join BLUE & BLACK 0V and join both WHITES 110V.
(Isolate RED & Isolate BROWN)

If the White leads are cut short please ensure the TWO wires are joined together in BOTH cases.