8720

	BLUE	VO			(V ORANGE		0.08A
(1))		(250	V GREY		0.00A
)))		500	V ORANGE		
	RED	115V)	İ	(V YELLOW	(1)	2A
	KED	1134	/		(ct	GREEN		
	BLACK	0V)		(
))		(6.3	3V YELLOW	(1)	
)		(V YELLOW	(2)	1A
))		(6.3	3V YELLOW	(2)	
	BROWN	115V)					

For 230V: Join RED & BLACK. Use BLUE & BROWN

For 115V: Join BLUE & BLACK OV and join RED & BROWN 115V.

<u>Note:</u> A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber casket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.