8996

				Ш	- 1					
	BLUE	0V)		ļ	(0V	ORANGE		
(1))			(300V	ORANGE		0.06A
	RED	115V)			(0V	YELLOW	(1)	2A
(2)	BLACK	0V				(6.3V	YELLOW	(1)	ZA
	BLACK	0 0)		ļ	(0V	YELLOW	(2)	2A
	BROWN	115V)			(ct		GREEN	ZA	
			,	 		(6.3V	YELLOW	(2)	
				ı I	- 1					

For 230V: Join RED & BLACK. Use BLUE & BROWN

For 115V: Join BLUE & BLACK OV and join RED & BROWN 115V.

 $\underline{\text{Note:}}$ A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.