


9233



For 240V: Join RED & BLACK. Use BLUE & BROWN
(Isolate both GREY separately)

For 120V: Join BLUE & BLACK 0V and join RED & BROWN 120V.
(Isolate both GREYS)

For 100V: Join BLUE & BLACK 0V and join both GREYS 100V.
(Isolate RED & Isolate BROWN)

If the Grey leads are cut short please ensure the TWO wires are joined together in BOTH cases.

Note: A certain amount of mechanical hum is prevalent in mains transformers and can be amplified when bolting to your metal work. Therefore you may find a small rubber gasket or similar material is worth fitting to quieten this hum to its' minimum, but please ensure the frame is grounded to the supply safety earth.