UF58s

```
      YELLOW  anode 1______ ||| _______
                           )||||(        common RED
                           )||||(
3.5k ohm                   )||||(
Fixed bias                 )||||(
                         __)||||(
      ORANGE x 2---+HT--|__ |||(_______ 8 ohms BROWN
                           )||||(
                           )||||(
                           )||||(
                           )||||(
      PINK     anode 2_____)||||(_______16 ohms BLUE
                            |||
```

UF58 (U058) PP Output for EL34 Fixed Bias
3500 ohms Rla-a. 65 W at 50 Hz. For guitar amplifier. Will produce harmonic colouration on overload.
130 mA per side. 30 Hz to 30 kHz. Suitable for VOX AC50 4 Mk2. Size L
Secondary 16 ohms tapped at 8 ohms

PDF Created with deskPDF PDF Writer - Trial :: http://www.docudesk.com