UX58

```
YELLOW  anode 1______ ||| _______
                     )|||(        Common GREEN
                     )|||(
                     )|||(
                     )|||(
                   __)|||(                        Secondary
ORANGE x 2---+HT--|__ |||(_______ 4 ohms GREY
                     )|||(
                     )|||(
                     )|||(
                     )|||(
PINK     anode 2_____)|||(_______ 8 ohms BROWN
                      |||
```

UX58 PP Output for EL34 Fixed Bias
3500 ohms Rla-a. 65 W at 50 Hz.
Secondary 8 ohms tapped at 4 ohms
130 mA per side. 30 Hz to 30 kHz.
For guitar amplifier. Will produce harmonic colouration on overload.
Suitable for VOX AC50 4 Mk2 (Please check dimensions, package style and secondary option).
Size L

PDF Created with deskPDF PDF Writer - Trial :: http://www.docudesk.com