

SOWTER TYPE 1960 Telefunken V72 Input Transformer

Applications

Replacement for Telefunken type CTV72/1. Ratio 1+1:20 (50+50/47k) can be configured for 50 Ohms 1:20 or 200 Ohms 1:10 Internal electrostatic shield to ensure good common-mode rejection. 100% Mumetal core for maximum bandwidth with negligible distortion. Same as type 9610 with split primary. Mumetal can with colour coded leads.

